


| CATALOG | NUMBER |
|---------|--------|
| | |

FLEXRAIL2 – LOW VOLTAGE TRACK HEAD

SERIES HM-826





| Ordering Matrix | | | | |
|-----------------|---------------|----------------|--------|----|
| Series | Model | | Finish | |
| | | | | |
| НМ | 826 (50w max) | 826L (75w max) | PT | BZ |

Ordering Example (series number - model number - finish): HM-826L-PT

| Product Deta | ils | | S | pecification Features | | |
|--------------|--|--|---|---|--|--|
| Description: | Flexrail2 compatible low voltage track head with integral electronic transformer. Available in either a 50w or 75w version. Utilizes MR16 lamps. | | | | | |
| Materials: | Transformer case is molded G.E. Lexan, track assembly and head are die cast aluminum. Lamp socket is a ceramic bi-pin. Supplied with a clear glass lens. | | • | Architectural die-cast aluminum track head with ball and swivel aiming u- wand. | | |
| Transformer: | Electronic low voltage with auto-reset, soft start and short circuit protection features. Dimmable with electronic low voltage dimmers. | | • | Both transformer case and track head assembly are painted in a matching finish. | | |
| Aiming: | 350° horizontal rotation and 90° vertical aiming with integral ball and swivel mounting feature. | | | | | |
| Lamping: | 50w MR16 maximum with HM-826 model. | | • | Electronic transformer soft start feature is designed to protect lamps | | |
| | 75w MR16 maximum with HM-826L model. | | | from abrupt inrush current. The solid | | |
| Accessories: | The clear lens supplied with the 826 can be replaced with one colored lens or lens accessory. | | | state circuitry promotes cool and quied operation. | | |
| Finish: | Abrasion resistant platinum or bronze paint finish. | | | 5 year product warranty | | |
| | PT = Platinum metal finish | | • | 5 year product warranty. | | |
| | BZ = Designer Bronze metal finish | | | | | |
| Listing: | UL & CUL Listed. | | | | | |